HH1077

TACTICAL VHF



5W, 30-88 MHz VHF Handheld Transceiver



Tactical VHF Radio

Power in Your Hand

Datron's HH1077 is a compact and lightweight VHF/FM handheld transceiver that provides communications capability in the 30 to 88 MHz band.

The HH1077 offers 2,320 channels at 25 kHz spacing with 15 programmable preset channels available via the rotary knob and 100 additional channels available through the keypad.

RF power output levels of 500mW, 2W and 5W are user selectable.

The HH1077 offers VOX for hands-free operation and Whisper mode.

The radio configuration can be cloned from another radio.

The HH1077 offers an optional embedded voice scrambler* that provides an effective means of secure communications.

It is interoperable in FM clear-voice mode with the PRC1077, the Spectre-V® series (PRC2100/2150), the HH7700, and most other single-channel 30-88 MHz VHF/FM radios using a 150 Hz tone-squelch or CTCSS squelch

The HH1077 radio is easy to operate and is rugged and immersible by design.

Datron offers a standard capacity battery permitting up to 20 hours of uninterrupted service.

Features

- 15 Channels
- 150-Hz and CTCSS (PL) Squelch
- **Keypad/Display**
- **Optional Voice Scrambler**
- Hi/Mid/Low Power Levels
- **Rugged Construction per** MIL-STD-810
- Immersible per IP67
- **Full Range of Accessories**
- Easy to Operate
- **VOX Mode**
- **Whisper Mode**





Datron World Communications, Inc.

995 Joshua Way, Suite A Vista, CA, USA 92081

Tel: +1-760-597-1500 **Fax**: +1-760-597-1510

E-mail: sales@dtwc.com Web: http://www.dtwc.com



* Subject to export regulations

Specifications subject to change without notice - rev 200924

HH1077

5W, 30-88 MHz VHF Handheld Transceiver

GENERAL

• FREQUENCY RANGE:

· CCIR EMISSION TYPE:

MODE:

CHANNEL SPACING:

• TOTAL PRESET CHANNELS:

MODULATION:

DISPLAY:

PROGRAMMING:

· COMSEC:

CURRENT CONSUMPTION

TX-RX-Stdbv:

BATTERY LIFE:

HH-3900BAT:

ENVIRONMENTAL

• TEMPERATURE: · IMMERSION:

MECHANICAL

• SIZE (HxWxD includes HH3900BAT):

WEIGHT:

· COLOR:

RECEIVER

· RECEIVER TYPE:

 SENSITIVITY: · SQUELCH:

· AUDIO DISTORTION:

AUDIO OUTPUT:

OUTPUT IMPEDANCE:

TRANSMITTER

• OUTPUT POWER:

ANTENNA IMPEDANCE:

FREQUENCY STABILITY:

· FM HUM & NOISE:

• SPURIOUS RESPONSE:

MODULATION:

DISTORTION:

MAJOR ACCESSORIES

HH-3900BAT

HH-CHG2

HH-CHG3

HH-ANT1

HH-MIC2

HH-SCR1

30 MHz to 87.9875 MHz

26K0F3E (Wide)

SIMPLEX, HALF DUPLEX

25 kHz (Wide)

26K0F3E Wideband FM - Compatible with HH7700, PRC1077, and Spectre V

radios in FM mode

Alphanumeric LCD, 14 segments,

5 digits plus icons

Computer Programmable Optional Voice Scrambler*

Less than 2.5A @5W

Less than 0.6 A Less than 80 mA

3900 mAH Li-lon, 20 hours expected life

-30°C to +60°C

Immersible per IP67

5.5 in. x 2.7 in. x 1.8 in.

(13.97 cm x 6.36 cm x 4.57 cm)

1.12 lbs. with battery and belt clip Olive drab green

Dual Conversion, Super Heterodyne

Better than -116 dBm @ 12 dB SINAD

150-Hz Tone, CTCSS (39 tones)

≤ 5%

400mW (≤ 5% distortion), 500mW max.

Hi: 5W, Mid: 2W, Low: 500 mW (nominal)

± 2.5 ppm (-30°C to +60°C)

> 45 dB

< -35 dB

Direct frequency modulation

3.9 AH Li-lon battery

Battery charger

Mobile battery charger

Flexible 30-88 MHz antenna

Speaker/microphone

Voice Scrambler*

